

INTERNATIONAL STANDARD

NORME INTERNATIONALE

AMENDMENT 1
AMENDEMENT 1

Low-voltage switchgear and controlgear –
Part 2: Circuit-breakers

Appareillage à basse tension –
Partie 2: Disjoncteurs

Switchgear and controlgear



THIS PUBLICATION IS COPYRIGHT PROTECTED

Copyright © 2009 IEC, Geneva, Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either IEC or IEC's member National Committee in the country of the requester.

If you have any questions about IEC copyright or have an enquiry about obtaining additional rights to this publication, please contact the address below or your local IEC member National Committee for further information.

Droits de reproduction réservés. Sauf indication contraire, aucune partie de cette publication ne peut être reproduite ni utilisée sous quelque forme que ce soit et par aucun procédé, électronique ou mécanique, y compris la photocopie et les microfilms, sans l'accord écrit de la CEI ou du Comité national de la CEI du pays du demandeur.

Si vous avez des questions sur le copyright de la CEI ou si vous désirez obtenir des droits supplémentaires sur cette publication, utilisez les coordonnées ci-après ou contactez le Comité national de la CEI de votre pays de résidence.

IEC Central Office
3, rue de Varembe
CH-1211 Geneva 20
Switzerland
Email: inmail@iec.ch
Web: www.iec.ch

About the IEC

The International Electrotechnical Commission (IEC) is the leading global organization that prepares and publishes International Standards for all electrical, electronic and related technologies.

About IEC publications

The technical content of IEC publications is kept under constant review by the IEC. Please make sure that you have the latest edition, a corrigenda or an amendment might have been published.

- Catalogue of IEC publications: www.iec.ch/searchpub

The IEC on-line Catalogue enables you to search by a variety of criteria (reference number, text, technical committee,...). It also gives information on projects, withdrawn and replaced publications.

- IEC Just Published: www.iec.ch/online_news/justpub

Stay up to date on all new IEC publications. Just Published details twice a month all new publications released. Available on-line and also by email.

- Electropedia: www.electropedia.org

The world's leading online dictionary of electronic and electrical terms containing more than 20 000 terms and definitions in English and French, with equivalent terms in additional languages. Also known as the International Electrotechnical Vocabulary online.

- Customer Service Centre: www.iec.ch/webstore/custserv

If you wish to give us your feedback on this publication or need further assistance, please visit the Customer Service Centre FAQ or contact us:

Email: csc@iec.ch

Tel.: +41 22 919 02 11

Fax: +41 22 919 03 00

A propos de la CEI

La Commission Electrotechnique Internationale (CEI) est la première organisation mondiale qui élabore et publie des normes internationales pour tout ce qui a trait à l'électricité, à l'électronique et aux technologies apparentées.

A propos des publications CEI

Le contenu technique des publications de la CEI est constamment revu. Veuillez vous assurer que vous possédez l'édition la plus récente, un corrigendum ou amendement peut avoir été publié.

- Catalogue des publications de la CEI: www.iec.ch/searchpub/cur_fut-f.htm

Le Catalogue en-ligne de la CEI vous permet d'effectuer des recherches en utilisant différents critères (numéro de référence, texte, comité d'études,...). Il donne aussi des informations sur les projets et les publications retirées ou remplacées.

- Just Published CEI: www.iec.ch/online_news/justpub

Restez informé sur les nouvelles publications de la CEI. Just Published détaille deux fois par mois les nouvelles publications parues. Disponible en-ligne et aussi par email.

- Electropedia: www.electropedia.org

Le premier dictionnaire en ligne au monde de termes électroniques et électriques. Il contient plus de 20 000 termes et définitions en anglais et en français, ainsi que les termes équivalents dans les langues additionnelles. Egalement appelé Vocabulaire Electrotechnique International en ligne.

- Service Clients: www.iec.ch/webstore/custserv/custserv_entry-f.htm

Si vous désirez nous donner des commentaires sur cette publication ou si vous avez des questions, visitez le FAQ du Service clients ou contactez-nous:

Email: csc@iec.ch

Tél.: +41 22 919 02 11

Fax: +41 22 919 03 00



IEC 60947-2

Edition 4.0 2009-01

INTERNATIONAL STANDARD

NORME INTERNATIONALE

AMENDMENT 1

AMENDEMENT 1

Low-voltage switchgear and controlgear –
Part 2: Circuit-breakers

Appareillage à basse tension –
Partie 2: Disjoncteurs

SWITCHGEAR AND CONTROLGEAR

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

COMMISSION
ELECTROTECHNIQUE
INTERNATIONALE

PRICE CODE
CODE PRIX

U

ICS 29.130.20

ISBN 978-2-88910-336-2

FOREWORD

This amendment has been prepared by subcommittee 17B: Low-voltage switchgear and controlgear, of IEC technical committee 17: Switchgear and controlgear.

The text of this amendment is based on the following documents:

FDIS	Report on voting
17B/1636/FDIS	17B/1651/RVD

Full information on the voting for the approval of this amendment can be found in the report on voting indicated in the above table.

The committee has decided that the contents of this amendment and the base publication will remain unchanged until the maintenance result date indicated on the IEC web site under "http://webstore.iec.ch" in the data related to the specific publication. At this date, the publication will be

- reconfirmed;
- withdrawn;
- replaced by a revised edition, or
- amended.

Replace in the whole document "Utilization category" by "Selectivity category" except in Annex L.

CONTENTS

Add the following:

8.5 Special tests – Damp heat, salt mist, vibration and shock

Insert the following:

Figure K.2 – Template for characteristics of cut-off current versus prospective current from 1 kA to 200 kA

Figure K.3 – Template for characteristics of cut-off current versus prospective current from 0,01 kA to 200 kA

Figure K.4 – Template for characteristics of let-through energy versus prospective current from 1 kA to 200 kA

Figure K.5 – Template for characteristics of let-through energy versus prospective current from 0,01 kA to 200 kA

Figure K.6 – Example of the use of template K.2

Figure K.7 – Example of the use of template K.4

Insert the following:

Table 9b – Applicability of tests or test sequences to four-pole circuit-breakers in a given frame size and design when tested according to the alternative programme 1 of 8.3.1.4

Table 9c – Applicability of tests or test sequences to 3-pole circuit-breakers in a given frame size and design when tested according to the alternative programme 2 of 8.3.1.4

1.2 Normative references

Delete the reference to IEC 60364-4-41:2001.

Add the following reference:

IEC 60417, *Graphical symbols for use on equipment*

IEC 60617, *Graphical symbols for diagrams*

Replace “IEC 60755:1983” by “IEC/TR 60755:1983”.

Replace the reference to IEC 60947-1:2004 by the following:

IEC 60947-1:2007, *Low-voltage switchgear and controlgear – Part 1: General rules*

Add, after IEC 60947-4-1:2000, the following reference:

Amendment 2 (2005)

Replace the reference to IEC 61000-3-2:2000 by the following:

IEC 61000-3-2:2005, *Electromagnetic compatibility (EMC) – Part 3-2: Limits – Limits for harmonic current emissions (equipment input current ≤ 16 A per phase)*

Add, after IEC 61000-3-3:1994, the following reference:

Amendment 2 (2005)

Replace the reference to IEC 61000-4-3:2002 by the following:

IEC 61000-4-3:2006, *Electromagnetic compatibility (EMC) – Part 4-3: Testing and measurement techniques – Radiated, radio-frequency, electromagnetic field immunity test*

Replace the reference to IEC 61000-4-4:1995 by the following:

IEC 61000-4-4:2004, *Electromagnetic compatibility (EMC) – Part 4-4: Testing and measurement techniques – Electrical fast transient/burst immunity test*

Replace the reference to IEC 61000-4-5:1995 by the following:

IEC 61000-4-5:2005, *Electromagnetic compatibility (EMC) – Part 4-5: Testing and measurement techniques – Surge immunity test*

Add, after IEC 61000-4-6:2003, the following reference:

Amendment 2 (2006)

Replace “IEC 61000-5-2:1997” by “IEC/TR 61000-5-2:1997”

Add, after IEC 61008-1:1996, the following reference:

Amendment 2 (2006)

Add, after IEC 61009-1:1996, the following reference:

Amendment 2 (2006)

Add, after IEC 61009-1:1996, the following reference:

IEC 61131-1:2003, *Programmable controllers – Part 1: General information*

Add, after CISPR 11:2003, the following reference:

Amendment 2 (2006)

Add, after CISPR 22:2005, the following reference:

Amendment 2 (2006)

2.3 current-limiting circuit-breaker

Replace the existing definition by the following:

circuit-breaker that, within a specified range of current, prevents the let-through current reaching the prospective peak value and which limits the let-through energy (I^2t) to a value less than the let-through energy of a half-cycle wave of the symmetrical prospective current

NOTE 1 Reference may be made to either the symmetrical or asymmetrical prospective peak value of let-through current.

NOTE 2 The let-through current is also referred to as the cut-off current (see IEV 441-17-12).

NOTE 3 Templates for the graphical representation of the cut-off current characteristic and the let-through energy characteristic are given in Figures K.2 to K.5 and examples of the use of the templates in Figures K.6 and K.7.

Add, after definition 2.20, the following new definition 2.21:

**2.21
programmable logic controller
PLC**

digitally operating electronic system, designed for use in an industrial environment, which uses a programmable memory for the internal storage of user-oriented instructions for implementing specific functions such as logic, sequencing, timing, counting and arithmetic, to control, through digital or analogue inputs and outputs, various types of machines or processes. Both the PLC and its associated peripherals are designed so that they can be easily integrated into an industrial control system and easily used in all their intended functions

[IEC 61131-1, definition 3.5]

3.8

Replace the reference to 7.1.11 of IEC 60947-1 by the reference to 7.1.12 of IEC 60947-1.

4.3.2.4 Current rating for four-pole circuit-breakers

Replace the reference to 7.1.8 of IEC 60947-1 by the reference to 7.1.9 of IEC 60947-1.

5.2 Marking

Replace, under item a), last bullet, the reference to 7.1.5.1 of IEC 60947-1 by the reference to 7.1.6.1 of IEC 60947-1.

Correct, under item b), 7th bullet, the symbol ----- with the symbol ——

Replace, under item b), 13th bullet, the reference to 7.1.9.3 of IEC 60947-1 by the reference to 7.1.10.3 of IEC 60947-1.

Replace, under item e), the reference to 7.1.7.4 of IEC 60947-1 by the reference to 7.1.8.4 of IEC 60947-1.

7.1 Constructional requirements

Replace the five first paragraphs of the subclause by the following:

Subclause 7.1 of IEC 60947-1 applies. Where, in Subclause 7.1.2.2 of IEC 60947-1, the test temperature is to be specified, the test temperature required by this standard is 960°C.

7.1.2 Additional requirements for circuit-breakers suitable for isolation

Replace, in the second paragraph, the reference to 7.1.6 of IEC 60947-1 by the reference to 7.1.7 of IEC 60947-1.

7.1.5 List of construction breaks

Add a new item f).

- f) in the case of the 4-pole variant, replacement of the trip unit in the 4th pole by a link, to provide an unprotected neutral.

7.1.6 Additional requirements for circuit-breakers provided with a neutral pole

Replace, in the first paragraph, the reference to 7.1.8 of IEC 60947-1 by the reference to 7.1.9 of IEC 60947-1.

Add, after Subclause 7.1.6, the following new Subclause 7.1.7:

7.1.7 Digital inputs and outputs for use with programmable logic controllers (PLCs)

Annex S of IEC 60947-1 applies. For the purposes of this standard this requirement does not apply to digital inputs and outputs dedicated to devices other than PLCs.

8.1.1

Add, after the second dashed item, the following new third dashed item:

- special tests (see 8.5).

8.3.1 Test sequences

Replace the first four paragraphs of this subclause by the following:

8.3.1.1 General

Type tests are grouped together in a number of sequences, as shown in Table 9.

For each sequence, tests shall be made in the order listed unless otherwise specified in this standard.

8.3.1.2 Tests omitted from sequence I and made separately

With reference to 8.1.1 of IEC 60947-1, the following tests of test sequence I (see 8.3.3) may be omitted from the sequence and made on separate samples:

- tripping limits and characteristics (8.3.3.1); in which case the sample(s) tested in the sequence shall be subjected to the tests of 8.3.3.1.3, at the maximum setting only and without the additional test of item b) to verify the time-current characteristic;
- test of dielectric properties (8.3.3.2);
- test of under-voltage releases of 8.3.3.3.2 (item c) and 8.3.3.3.3, to verify the requirements of 7.2.1.3 of IEC 60947-1, and tests of under-voltage releases at alternative frequencies (see 8.3.2.1);
- test of shunt releases of 8.3.3.3.2 (item d) and 8.3.3.3.3, to verify the requirements of 7.2.1.4 of IEC 60947-1, and tests of shunt releases at alternative frequencies (see 8.3.2.1);
- additional tests for operational capability without current for withdrawable circuit-breakers (8.3.3.3.5).

8.3.1.3 Applicability of sequences according to the relationship between short-circuit ratings

The applicability of test sequences according to the relationship between I_{cs} , I_{cu} and I_{cw} is given in Table 9a.

Table 9 – Overall schema of test sequences ^a

Replace, in the fifth row (sequence V), third column:

- “Short-circuit at take-over current” by “Short-circuit at 1,1 times the take-over current”, and
- “Short-circuit at rated ultimate short-circuit braking capacity” by “Short-circuit at rated ultimate short-circuit breaking capacity”.

Replace footnote b by:

- b Except where Sequence VI is applied.

Replace, in footnote c, the 2nd dashed item by:

- where Sequence VI is applied