

INTERNATIONAL STANDARD

NORME INTERNATIONALE

**Railway applications – Rolling stock –
Protective provisions against electrical hazards**

**Applications ferroviaires – Matériel roulant –
Dispositions de protection contre les dangers électriques**





THIS PUBLICATION IS COPYRIGHT PROTECTED

Copyright © 2019 IEC, Geneva, Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either IEC or IEC's member National Committee in the country of the requester. If you have any questions about IEC copyright or have an enquiry about obtaining additional rights to this publication, please contact the address below or your local IEC member National Committee for further information.

Droits de reproduction réservés. Sauf indication contraire, aucune partie de cette publication ne peut être reproduite ni utilisée sous quelque forme que ce soit et par aucun procédé, électronique ou mécanique, y compris la photocopie et les microfilms, sans l'accord écrit de l'IEC ou du Comité national de l'IEC du pays du demandeur. Si vous avez des questions sur le copyright de l'IEC ou si vous désirez obtenir des droits supplémentaires sur cette publication, utilisez les coordonnées ci-après ou contactez le Comité national de l'IEC de votre pays de résidence.

IEC Central Office
3, rue de Varembe
CH-1211 Geneva 20
Switzerland

Tel.: +41 22 919 02 11
info@iec.ch
www.iec.ch

About the IEC

The International Electrotechnical Commission (IEC) is the leading global organization that prepares and publishes International Standards for all electrical, electronic and related technologies.

About IEC publications

The technical content of IEC publications is kept under constant review by the IEC. Please make sure that you have the latest edition, a corrigendum or an amendment might have been published.

IEC publications search - webstore.iec.ch/advsearchform

The advanced search enables to find IEC publications by a variety of criteria (reference number, text, technical committee,...). It also gives information on projects, replaced and withdrawn publications.

IEC Just Published - webstore.iec.ch/justpublished

Stay up to date on all new IEC publications. Just Published details all new publications released. Available online and once a month by email.

IEC Customer Service Centre - webstore.iec.ch/csc

If you wish to give us your feedback on this publication or need further assistance, please contact the Customer Service Centre: sales@iec.ch.

Electropedia - www.electropedia.org

The world's leading online dictionary on electrotechnology, containing more than 22 000 terminological entries in English and French, with equivalent terms in 16 additional languages. Also known as the International Electrotechnical Vocabulary (IEV) online.

IEC Glossary - std.iec.ch/glossary

67 000 electrotechnical terminology entries in English and French extracted from the Terms and Definitions clause of IEC publications issued since 2002. Some entries have been collected from earlier publications of IEC TC 37, 77, 86 and CISPR.

A propos de l'IEC

La Commission Electrotechnique Internationale (IEC) est la première organisation mondiale qui élabore et publie des Normes internationales pour tout ce qui a trait à l'électricité, à l'électronique et aux technologies apparentées.

A propos des publications IEC

Le contenu technique des publications IEC est constamment revu. Veuillez vous assurer que vous possédez l'édition la plus récente, un corrigendum ou amendement peut avoir été publié.

Recherche de publications IEC -

webstore.iec.ch/advsearchform

La recherche avancée permet de trouver des publications IEC en utilisant différents critères (numéro de référence, texte, comité d'études,...). Elle donne aussi des informations sur les projets et les publications remplacées ou retirées.

IEC Just Published - webstore.iec.ch/justpublished

Restez informé sur les nouvelles publications IEC. Just Published détaille les nouvelles publications parues. Disponible en ligne et une fois par mois par email.

Service Clients - webstore.iec.ch/csc

Si vous désirez nous donner des commentaires sur cette publication ou si vous avez des questions contactez-nous: sales@iec.ch.

Electropedia - www.electropedia.org

Le premier dictionnaire d'électrotechnologie en ligne au monde, avec plus de 22 000 articles terminologiques en anglais et en français, ainsi que les termes équivalents dans 16 langues additionnelles. Egalement appelé Vocabulaire Electrotechnique International (IEV) en ligne.

Glossaire IEC - std.iec.ch/glossary

67 000 entrées terminologiques électrotechniques, en anglais et en français, extraites des articles Termes et Définitions des publications IEC parues depuis 2002. Plus certaines entrées antérieures extraites des publications des CE 37, 77, 86 et CISPR de l'IEC.



IEC 61991

Edition 2.0 2019-05

INTERNATIONAL STANDARD

NORME INTERNATIONALE

**Railway applications – Rolling stock –
Protective provisions against electrical hazards**

**Applications ferroviaires – Matériel roulant –
Dispositions de protection contre les dangers électriques**

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

COMMISSION
ELECTROTECHNIQUE
INTERNATIONALE

ICS 45.060.01

ISBN 978-2-8322-6596-3

**Warning! Make sure that you obtained this publication from an authorized distributor.
Attention! Veuillez vous assurer que vous avez obtenu cette publication via un distributeur agréé.**

CONTENTS

FOREWORD.....	4
INTRODUCTION.....	6
1 Scope.....	7
2 Normative references	7
3 Terms, definitions and abbreviated terms	8
3.1 Terms and definitions.....	8
3.1.1 Definitions concerning persons	8
3.1.2 Other definitions	8
3.2 Abbreviated terms.....	12
4 Classification of voltage bands	12
4.1 General principles.....	12
4.2 Connections between circuits.....	13
4.3 Exceptions	13
5 Protective provisions against direct contact	14
5.1 General.....	14
5.2 Protection by insulation.....	14
5.3 Protection by prevention of access.....	14
5.3.1 Voltages in bands I to III.....	14
5.3.2 Voltages in band IV	15
5.4 Protection by the use of band I (ELV).....	16
5.4.1 Requirements for systems of band I (SELV and PELV).....	16
5.4.2 Additional requirements for SELV	16
5.4.3 Additional requirements for PELV	16
5.5 Warning labels.....	16
6 Protective provisions against indirect contact	17
6.1 General.....	17
6.2 Protective bonding	17
6.2.1 General	17
6.2.2 Equipotential bond.....	17
6.2.3 Protective bonding rating	17
6.2.4 Sliding contacts	18
6.3 Disconnection of the supply	18
6.3.1 Application.....	18
6.3.2 Disconnection characteristic	18
6.4 Main protective bonding	18
6.4.1 General	18
6.4.2 Bonding paths	18
6.4.3 Impedance.....	19
6.4.4 Contact line fault	20
6.5 Clarifications and exceptions with reference to indirect contact.....	20
6.5.1 Parts requiring protective provisions	20
6.5.2 Parts not requiring protective provisions	20
6.5.3 Multi-stage insulation.....	20
6.5.4 Floating supplies	21
6.5.5 Insulated wheel or levitation systems without a protective conductor	21
6.6 Additional requirements – Bearings.....	21

7	Power circuit.....	21
7.1	General principles.....	21
7.2	Power circuit insulated from the vehicle body or bogie.....	22
7.3	Power circuit using the vehicle body or bogie.....	22
8	Additional requirements.....	22
8.1	General.....	22
8.2	Current collectors.....	22
8.3	Capacitors.....	22
8.4	Plug and socket devices.....	23
8.4.1	Portable apparatus.....	23
8.4.2	Vehicle and intervehicle connectors.....	23
8.5	Special sources.....	24
8.5.1	General.....	24
8.5.2	Live parts not requiring protective provisions.....	24
8.5.3	Live parts requiring protective provisions.....	24
	Annex A (normative) List of items where contracting parties shall co-operate.....	25
	Annex B (informative) Special national conditions.....	26
B.1	General.....	26
B.2	France.....	26
B.3	Great Britain.....	26
B.3.1	Operate over 750 V DC third rail electrified lines.....	26
B.3.2	Bonding between rail vehicle main body to bogie.....	26
B.3.3	Intervehicle bonding.....	27
B.4	Japan.....	27
B.4.1	General.....	27
B.4.2	[6.4.4] Contact line fault.....	27
B.4.3	[8.4.1] Portable apparatus.....	27
	Annex C (informative) Example solutions for impedance management in electric multiple units (EMUs).....	28
C.1	Preventing absorption of return current in EMUs.....	28
C.2	Examples of solutions.....	29
	Bibliography.....	30
	Figure C.1 – Concentration of return current.....	28
	Figure C.2 – Attach earth resistors for long-length EMUs preventing current absorption.....	28
	Table 1 – Voltage bands.....	13
	Table 2 – Maximum impedance between each vehicle body of a unit and protective conductor of the fixed installation.....	19
	Table B.1 – Voltage bands.....	26

INTERNATIONAL ELECTROTECHNICAL COMMISSION

**RAILWAY APPLICATIONS – ROLLING STOCK –
Protective provisions against electrical hazards****FOREWORD**

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as “IEC Publication(s)”). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

International Standard IEC 61991 has been prepared by IEC technical committee 9: Electrical equipment and systems for railways.

This second edition cancels and replaces the first edition, published in 2000. This edition constitutes a technical revision. It is based on EN 50153:2014.

This edition includes the following significant technical changes with respect to the previous edition:

- a) Replacement of several reference standards.
- b) Several terms and abbreviated terms are introduced;
- c) Table 2 – Voltage bands for France is moved to Annex B as Table B.1, Table 3 – Voltage bands for Italy is deleted;
- d) Annex B and Annex C are introduced.
- e) Annex B includes special national conditions.

The text of this International Standard is based on the following documents:

FDIS	Report on voting
9/2467/FDIS	9/2487/RVD

Full information on the voting for the approval of this International Standard can be found in the report on voting indicated in the above table.

This document has been drafted in accordance with the ISO/IEC Directives, Part 2.

The committee has decided that the contents of this document will remain unchanged until the stability date indicated on the IEC website under "<http://webstore.iec.ch>" in the data related to the specific document. At this date, the document will be

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

INTRODUCTION

It is generally accepted that safety depends on human factors, based on the normal behaviour of the operators involved, as well as upon technical factors.

For these reasons, this document leaves a choice to the contracting parties between two alternatives in several instances. These alternatives consist of either the provision of operating rules, regulations and procedures, or the application of technical measures such as mechanical or electrical interlocking devices.

A list of the cases for which the contracting parties (e.g. user and manufacturer) shall reach agreement before signing the contract is included in Annex A.

RAILWAY APPLICATIONS – ROLLING STOCK –

Protective provisions against electrical hazards

1 Scope

This document defines requirements applied in the design and manufacture of electrical installations and equipment to be used on rolling stock to protect persons from electric shocks.

This document is applicable to rolling stock of rail transport systems, road transport systems if they are powered by an external supply (e.g. trolley buses), magnetically levitated transport systems, and to the electrical equipment installed in these systems.

This document does not apply to:

- mine railways in mines,
- crane installations, moving platforms and similar transport systems on rails,
- funicular railways,
- temporary constructions.

The requirements for the fixed installations about the protection against the vehicles' potential are not covered in this document.

2 Normative references

The following documents are referred to in the text in such a way that some or all of their content constitutes requirements of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60364-4-41:2005, *Low-voltage electrical installations – Part 4-41: Protection for safety – Protection against electric shock*

IEC TS 60479-1, *Effects of current on human beings and livestock – Part 1: General aspects*

IEC 60529, *Degrees of protection provided by enclosures (IP Code)*

IEC 61140:2016, *Protection against electric shock – Common aspects for installation and equipment*

IEC 61310-1, *Safety of machinery – Indication, marking and actuation – Part 1: Requirements for visual, acoustic and tactile signals*

IEC 62128-1:2013, *Railway applications – Fixed installations – Electrical safety, earthing and the return circuit – Part 1: Protective provisions against electric shock*

IEC 62313, *Railway applications – Power supply and rolling stock – Technical criteria for the coordination between power supply (substation) and rolling stock*

IEC 62497-1, *Railway applications – Insulation coordination – Part 1: Basic requirements – Clearances and creepage distances for all electrical and electronic equipment*

IEC 62995:2018, *Railway applications – Rolling Stock – Rules for installation of cabling*

3 Terms, definitions and abbreviated terms

3.1 Terms and definitions

For the purposes of this document, the following terms and definitions apply.

ISO and IEC maintain terminological databases for use in standardization at the following addresses:

- IEC Electropedia: available at <http://www.electropedia.org/>
- ISO Online browsing platform: available at <http://www.iso.org/obp>

NOTE For more information relating to definitions of parts of the fixed installations, refer to IEC 62128-1 from which these definitions are derived.

3.1.1 Definitions concerning persons

3.1.1.1

<electrically> instructed person

person adequately advised or supervised by electrically skilled persons to enable him or her to perceive risks and to avoid hazards which electricity can create

[SOURCE: IEC 60050-195:1998, 195-04-02]

3.1.1.2

ordinary person

person who is neither a skilled person nor an instructed person

[SOURCE: IEC 60050-195:1998, 195-04-03]

3.1.1.3

<electrically> skilled person

person with relevant education and experience to enable him or her to perceive risks and to avoid hazards which electricity can create

[SOURCE: IEC 60050-195:1998, 195-04-01]

3.1.2 Other definitions

3.1.2.1

closed electrical operating area

room or location which serves exclusively for the operation of electrical equipment and is kept secure by a means appropriate to the voltage and location

Note 1 to entry: Access to such areas is permitted only to (electrically) skilled persons and (electrically) instructed persons.

Note 2 to entry: The definition of closed electrical operating area can be suitable for underfloor or upperroof cabinets. Generally speaking, it is any location (inside or outside the car body) which is kept secured because of the voltage that can be assumed to be present on the equipment inside it. Access to such areas is not allowed for ordinary persons.

3.1.2.2

contact line

conductor system for supplying electrical energy to rolling stock through current-collecting equipment

[SOURCE: IEC 60050-811:2017, 811-33-01, modified – The term “vehicle” has been replaced by “rolling stock” and Note 1 to entry has been omitted.]

3.1.2.3

contact wire

electric conductor of an overhead contact line with which the current collectors make contact

[SOURCE: IEC 60050-811:2017, 811-33-15]

3.1.2.4

direct contact

electric contact of persons or animals with live parts

[SOURCE: IEC 60050-195:1998, 195-06-03]

3.1.2.5

double insulation

insulation comprising both basic insulation and supplementary insulation

[SOURCE: IEC 60050-195:1998, 195-06-08]

3.1.2.6

earth

conductive mass of the earth, whose electrical potential at any point is conventionally taken as equal to zero

3.1.2.7

electrical operating area

room or location which serves primarily for the operation of electrical equipment and is normally entered only by skilled persons or (electrically) instructed persons

Note 1 to entry: Generally speaking, an electrical operating area is any location (mainly inside the car body) where electrical equipment operates. The above is the main function of this area but not the only one. In fact, normally the area is not kept secured and protection against direct contact is achieved by other means (e.g. (electrically) protective obstacles).

3.1.2.8

electric shock

physiological effect resulting from an electric current passing through a human or animal body

[SOURCE: IEC 60050-195:1998, 195-01-04]

3.1.2.9

extra-low voltage

voltage not exceeding the relevant voltage limit of band II specified in Table 1

[SOURCE: IEC 60050-826:2004, 826-12-30, modified – The term “band I” has been replaced by “band II” and “IEC 60449” has been replaced by “Table 1”.]

3.1.2.10

equipotential bond

electrical connection putting various exposed conductive parts at a substantially equal potential

Note 1 to entry: This can be abbreviated as ‘bond’ or ‘bonding’.

3.1.2.11

exposed conductive part <of electrical equipment>

conductive part of electrical equipment, which can be touched and which is not normally live, but can become live when basic insulation fails

Note 1 to entry: A conductive part of electrical equipment which can only become live through contact with an exposed conductive part which has become live is not considered to be an exposed conductive part itself.

3.1.2.12

indirect contact

electric contact of persons or animals with exposed conductive parts which have become live under fault conditions

[SOURCE: IEC 60050-195:1998, 195-06-04]

3.1.2.13

interlocking device

device which makes the operation of a switching device dependent upon the position or operation of one or more other pieces of equipment

[SOURCE: IEC 60050-441:2000, 441-16-49]

3.1.2.14

insulate, verb

prevent electric conduction between conductive elements by means of insulating materials

[SOURCE: IEC 60050-151:2001, 151-15-36]

3.1.2.15

insulation

all the materials and parts used to insulate conductive elements of a device

[SOURCE: IEC 60050-151:2001, 151-15-41]

3.1.2.16

live part <in electric traction>

conductor or conductive part intended to be energized in normal use

Note 1 to entry: This concept does not necessarily imply a risk of electric shock.

Note 2 to entry: By convention, this does not include the running rails and parts connected to them.

[SOURCE: IEC 60050-811:2017, 811-36-23]

3.1.2.17

locking system

system which comprises interlocking devices and physically prevents access to live parts unless the supply of electrical energy to the live parts has been isolated and made safe

3.1.2.18

mechanical locking

use of a lock or bolted /screwed fixings to prevent access panels or doors being opened and require the use of a key or tool to remove

3.1.2.19

multi-stage insulation

insulation system having more than one stage of insulation and an intermediate frame between consecutive stages

[SOURCE: IEC 60322:2001, 3.4, modified – Notes have been deleted.]

3.1.2.20

nominal voltage <of a system>

suitable approximate value of voltage used to designate or identify a system

Note 1 to entry: The voltages are expressed by the value between poles, ripple-free for DC and by the RMS value between phases for AC.

Note 2 to entry: The actual voltage can differ from the nominal voltage by a quantity within permitted tolerances. For further information about traction systems supply voltages, see IEC 60850.

[SOURCE: IEC 60050-601:1985, 601-01-21, modified – Notes to entry have been added.]

3.1.2.21

PELV system

electric system in which the voltage cannot exceed the value of extra-low voltage:

- under normal conditions and
- under single fault conditions, except earth faults in other electric circuits

[SOURCE: IEC 60050-826:2004, 826-12-32, modified – Note has been deleted.]

3.1.2.22

<electrically> protective obstacle

part preventing unintentional direct contact, but not preventing direct contact by deliberate action

[SOURCE: IEC 60050-195:1998, 195-06-16]

3.1.2.23

power circuit

circuit carrying the current of the machines and equipment, such as the converters and traction motors, which transmit the traction output

[SOURCE: IEC 60050-811:2017, 811-25-03]

3.1.2.24

protective conductor

conductor provided for purposes of safety, for example protection against electric shock

[SOURCE: IEC 60050-195:1998, 195-02-09]

3.1.2.25

protective-equipotential-bonding

equipotential bonding for the purposes of safety

[SOURCE: IEC 60050-195:1998, 195-01-15]

3.1.2.26

SELV system

electric system in which the voltage cannot exceed the value of extra-low voltage:

- under normal conditions and
- under single fault conditions, including earth faults in other electric circuits

[SOURCE: IEC 60050-826:2004, 826-12-31, modified – Note has been deleted.]

3.1.2.27

total insulation

insulation composed of basic insulation as provision for basic protection, and supplementary insulation as provision for fault protection, or providing basic and fault protection by reinforced insulation, in accordance with IEC 61140:2016, 7.4

[SOURCE: IEC 60050-851:2008/AMD1:2014, 851-15-11, modified – “equipment with” has been replaced with “insulation composed of” and “IEC 61140:2011,7.3” has been replaced with “IEC 61140:2016,7.4”.]

3.1.2.28

Unit <electrically connected>

minimum operational formation comprising one or more vehicles coupled together

3.2 Abbreviated terms

AC	Alternating Current
DC	Direct Current
ELV	Extra Low Voltage
EMU	Electric Multiple Unit
PELV	Protective Extra Low Voltage
RMS	root-mean-square value (effective value)
SELV	Safety Extra Low Voltage

4 Classification of voltage bands

4.1 General principles

In this document, the applicable protective measures are based on the highest value of the nominal supply voltage which the equipment or the electrical circuits are subjected to.

The voltages are classified into bands according to the nominal value as shown in Table 1. Different rules apply to each of these bands.

The power supply of the various circuits installed in railway rolling stock can be from different sources such as:

- batteries,
- transformers,
- voltage dividers,
- rotating machines,
- static converters,
- capacitors,
- special sources.